

Title of the invention

OPTICAL SIGHT

Background of the invention**Field of the invention**

The invention relates to an optical sight used for example on a hunting weapon such as a hunting gun. The invention more particularly relates to a sight in which a light source creates a light spot which is superimposed on a target which is viewed through the sight.

Description of related art

Weapon sights comprising a light channel, a lens at one end of the light channel, having a partially reflecting surface, a light emitting diode (LED), and a battery for energising the light source have been available for approximately 20 years. In these sights, the energised LED emits light towards the reflecting surface of the lens to produce an image of a light spot which can be superimposed on a target when sighting through the light channel from the other end thereof. The intensity of the light spot is varied by altering the drive current of the LED.

The main problem with these sights is low battery life (approximately four hours of continuous use at the brightest spot intensity). As a result, the user must replace the battery at regular intervals. This can lead to various practical problems especially if the user is in some remote location and batteries are not readily available. Further, since the sight can be used in extreme conditions, the battery compartment must be made as a watertight enclosure which can be opened. This adds to production costs and generally reduces the overall robustness of the sight.

SE-B-378 450 and SE-B-449 262 teach that in order to save energy, the LED should be pulsed. Although such an arrangement increases the battery life of the sight, the resulting sight still has a low battery life of approximately forty hours of continuous use at the brightest spot intensity.

Brief summary of the invention

a The optical sight of the invention comprises an elongate housing defining a light channel, a lens located at one end of the light channel and having a partially reflecting surface, a light source for emitting light towards ~~said~~^{the} reflecting surface to produce an image of a light spot which is superimposed on a target when sighting through the light channel from the other end thereof, a battery for providing electric current, and an energising circuit for energising ~~said~~^{the} light source operable to apply a pulsating electric current from ~~said~~^{the} battery to said light source, for causing the light source to emit pulses of light.

a According to the invention, in order to increase many times the battery life in an optical sight of this kind, a laser diode is provided as the light source therein. By using a laser diode the sight can be made substantially maintenance-free having a battery life of over 5000 hours of continuous use.

a In the presently preferred embodiment of the sight according to the invention, control means are provided for energising the laser diode when the weapon is to be used and for automatically reducing energisation of the laser diode in dependence of a predetermined condition.

Reduced energisation of the laser diode also includes the condition wherein the laser diode is completely turned off.

In the presently preferred embodiment of the sight according to this invention, control means are incorporated to vary the intensity of the light spot.

The invention yields a significant increase of the overall efficiency of the sight because the laser diode has an electrical-to-(useful)optical efficiency, i. e. the efficiency in converting electric energy into useful optical energy which is used to produce the light seen by the user, which is considerably higher than the electrical-to-(useful)optical efficiency of a conventional LED as used in existing sights. Moreover, if the laser diode is energised only periodically, viz. during the periods when a weapon on which the sight is mounted, is in use or is ready for use, the battery will last for years, maybe for the lifetime of the sight, and therefore can be mounted in a permanently closed space in the sight so as to be exchanged only in the sight factory, e.g. in connection with maintenance service on the sight, no battery exchange being necessary in the field.

Brief description of the drawings

In order to explain the invention in more detail an illustrative embodiment thereof will be described below reference being made to the accompanying drawings in which

FIG 1 is an axial sectional view of a sight of the invention,

FIG 2 is a cross sectional view along line II - II in FIG 1,

FIG 3 is a block diagram of a complete electronics configuration for driving the laser diode and varying the intensity of the light spot via pulse width modulation,

FIG 4 is a similar block diagram as that in FIG 3 including also means for reducing the energisation of the laser diode via the use of a predetermined time-out of the sight of the invention, and

FIG 5 is a block diagram showing the interaction of a deenergisation sensor, which determines when the gun to which the sight is attached is in use, with the drive electronics for the laser diode.

Detailed description of the invention

The weapon sight disclosed in FIG 1 comprises a light tunnel formed by an outer tube 10 to be fastened to the barrel of a weapon on which the sight shall be used, and an inner tube 11 which is mounted in the outer tube at one end and is fixed at the other end by adjustment means allowing adjustment of the longitudinal axis of the inner tube in relation to the longitudinal axis of the outer tube as is necessary in order to adapt the sight to the weapon on which it is used. In ~~said~~^{the} one end of the inner tube a double lens 12 is provided having a layer 13 between the lenses, ~~said~~^{the} layer reflecting red light. Inside the inner tube a light source 14 comprising a laser diode is mounted which projects a beam of red light on the layer 13 which reflects the light beam through a face-ground glass plate 15 having an anti-reflexion layer on the side thereof facing the right end of the light tunnel. The light path is indicated by a dot-and-dash line 16 in FIG 1. The laser diode is energised via electronic drive circuitry by a battery 17 mounted in a closed housing 18 integral with the outer tube 10 and located e.g. on the side thereof as shown in FIG 2, the battery being electrically connected with the drive electronics for the laser diode by conductors (not shown). A

suitable battery for use in the sight of the invention is a lithium cell DL1/3N having a capacity of 160 mAh.

A representative laser diode for use in the sight of the invention is Sony SLD1122VS generating an optical output power of 5 mW at a forward current of 50 mA and a forward voltage of 2.2 V. The input power is therefore 110 mW and the electrical-to-optical efficiency 4.5 %. This laser diode converts electric energy to useful optical energy 4500 times better than the existing conventional LED. There are two main reasons for this. The first reason is that a laser diode fundamentally has a better efficiency than an LED wherein a proportion of the generated light is trapped inside the diode by total internal reflection, is reabsorbed and causes the LED to heat up. This does not happen in the laser diode. The second reason is that the conventional LED is used with a metal mask placed in front of the LED to reduce the size of the light source and consequently the size of the beam emitted therefrom. The mask causes a significant amount of the output power of the LED to be wasted. It is not necessary to mask the laser diode in this manner, since it is an inherently small source. For example, the Sony SLD1122VS has a source size of $1\mu\text{m}$ by $3\mu\text{m}$.

The intensity of the light spot in existing sights is varied by altering the drive current of the LED. Varying the light spot intensity in the weapon sight of the present invention is not best done in this simple manner. The use of a laser diode introduces a complication due to the laser light-current characteristic. There is a threshold current below which the laser diode does not lase. Control of the output power of the laser diode by control of the drive current in the manner applied with an LED is difficult, particularly for low output power. This is because the

threshold current varies from one laser diode to the other and is also temperature dependent. Therefore, a better solution is to drive the laser diode into the lasing region and to control the output power of the laser diode by means of pulse width modulation.

If it is assumed that an average optical power output of 1 μW is typical for an LED used in a sight to produce the brightest spot intensity, then it is necessary to drive the laser diode at a duty cycle of 1 $\mu\text{W}/5 \text{ mW} = 2 \times 10^{-4}$. The average current taken by the laser diode to produce the brightest spot intensity is then $2 \times 10^{-4} \times 50 \text{ mA} = 10 \mu\text{A}$.

FIG 3 shows a block diagram of a circuit according to this technique. The laser diode 14 is driven with pulses from a programmable pulse generator 19 powered from the battery 17 via a laser diode driver power control 20. The brightness of the laser diode is varied by changing the pulse length in accordance with the present invention. The user sets the desired spot brightness using a multi-position switch 21 which controls an oscillator 22 connected to the pulse generator 19.

An alternative embodiment of the circuit is disclosed in FIG 4, which incorporates an automatic time-out mechanism to reduce the energisation of the laser diode after a pre-determined length of time. This further increases the operational lifetime of the sight since there will be significant periods of time when there is little or no current consumption. The oscillator is replaced by a micro-controller 22' which reads the position of the switch 21 and sets the correct pulse length according to values in a look-up table stored in an EEPROM 23. When the unit is not in use, a micro-controller power control 24 powers the micro-controller 22' approximately once every second.

If the switch position has not changed since the unit was last used, the micro-controller resets a timer 25 and the power controller 24 turns off the power. If the switch position has changed, then the unit has started to be used. In this situation the micro-controller 22' continuously triggers the programmable pulse generator 19 at a rate sufficient that the pulsing of the laser light is not evident to the user. The rate would typically be around 200 Hz. The timer 25 is reset by changes in the position of the switch 21 and is used to implement a time-out function. If a pre-determined period has elapsed before the position of switch 21 has changed, it is assumed that the sight is no longer in use and that it can be switched off by micro-controller 22'. The period of this time-out would typically be several hours. For a period before the end of the time-out period, the micro-controller 22' causes the laser diode to pulse at a low rate, visible to the user, so as to indicate to the user that the end of the time-out period is approaching. This warning period would typically be of the order of 10 seconds. If the user wishes to continue to use the sight, he moves the switch 21 by at least one position, causing the timer 25 to be reset via the micro-controller 22' and re-initiating the time-out period.

In a practical embodiment of the circuit described means should be provided to compensate for the change in laser diode characteristics with temperature. One possible way of achieving this would be to incorporate a thermistor into the circuit in series with the laser diode to provide a compensation in the current as the temperature changes. Furthermore, the circuit should be made fail safe such that any failure of the circuit leads to the laser diode being turned off. The eye of the person using the sight should not be exposed to an

emission from the laser diode which is over the maximum permissible exposure limit.

The most simple solution for controlling the electronic circuit in order to have the laser diode deenergised during periods when a weapon on which the sight is mounted is not used and to energise the laser diode when the weapon is to be used and during use thereof is to include in the electronic circuit a time-out circuitry, as mentioned above. When the laser diode has been turned on, which can be effected for example by the user pressing a conveniently located push button switch, the time-out circuitry would simply automatically turn the laser diode off after a predetermined length of time - say several hours - after the laser diode has been turned on. Then, the user would just press the button again if he wishes continued use of the sight. The laser diode will then be energised for the predetermined time period. The time-out circuitry can include means for setting different lengths of the time-out. The end of the time-out period may be indicated to the user by causing the laser to flash at a rate visible to the human eye for a predetermined period before the end of the time-out period.

The electronic circuit can also include a detector which senses vibration and motion as long as a weapon on which the sight is mounted, is held by a user. When the laser diode has been turned on by the user actuating a switch in order to bring the weapon into use the laser diode will be turned off by a switch controlled by the detector when vibration or motion is no longer sensed by the detector due to the weapon no longer being held by the user. The detector can comprise e. g. a piezoelectric element. The vibration or motion signal can be integrated over the time and

the laser diode can be turned off when the integrated signal falls below a predetermined threshold value.

Typically, weapons are stored in a different orientation to that in which they are shot. Either they may be stored vertically or lying on their side while they tend to be shot horizontally and upright. A tilt sensor can be provided to detect when the weapon is in a normal orientation for shooting and then the sensor can actuate a switch incorporated into the electronic circuit, in order to turn on the laser diode. When the weapon is put into a "non-shooting" position the laser diode will be turned off by the sensor actuated switch.

When a motion or vibration detector or a tilt sensor is provided for controlling energisation of the laser diode it may be desirable to have an override option which allows the laser diode to remain turned on also when no motion or vibration is detected or the weapon is in a "non-shooting" orientation. This override option can be protected by a time-out circuitry to prevent the laser diode from being left turned on unintentionally.

For daytime usage of a weapon on which the sight is mounted a photodiode for detecting ambient light could be included into the electronic circuit. When the ambient light is above a certain threshold level the laser diode should be turned on under the control of the photodiode, and when the ambient light is below ^{this} ~~said~~ threshold value the current to the laser diode is reduced to a minimum setting under the control of the photodiode. This will allow operation of the sight at night and will also reduce the power consumption to its minimum level when the weapon is stored in the dark. If the weapon is to be stored in a light area the laser diode should not of course be turned on by the photodiode under the influence of ambient light. In

this case the laser diode should be turned on by means of a manually operated switch possibly combined with a time-out function.

The laser diode requires to be turned on only when a user of a weapon on which the sight is mounted actually is looking through the sight. Therefore, a good method of determining when the sight is being used is to detect the presence of the eye. A low level IR source can be mounted inside the sight in the inner tube 11 thereof and facing towards the location of the eye. When the eye is present there would be reflection of the IR from the cornea and retina which can be detected to confirm the presence of a user. The red dot generated by the laser diode could itself be used as the illumination source which reflects off the eye. This solution requires less power since the sight would then contain only one light source. By pulsing the light source the reflected light could be distinguished from the ambient light.

The periodic blinking of the eye could be used as confirmation that the sight is being used. Combining detection of the eye reflection and the interruptions caused by blinking would enable reflection from inanimate items or other body parts to be distinguished.

The heat radiated from the user's face or the vibration introduced by the user's breathing also could be used for turning the laser diode on and off. For sensing the heat a temperature sensitive resistor can be mounted at the entrance of the sight. A motion or vibration sensor, such as a piezoelectric element or an accelerometer can be used as sensing element for the user's ^{breathing} ~~operating~~.

FIG 5 summarizes in a block diagram the different methods of controlling energisation of the sight. A

	1970	1971	1972	1973	1974	1975	1976	1977	1978	1979	1980	1981	1982	1983	1984	1985	1986	1987	1988	1989	1990	1991	1992	1993	1994	1995	1996	1997	1998	1999	2000	2001	2002	2003	2004	2005	2006	2007	2008	2009	2010	2011	2012	2013	2014	2015	2016	2017	2018	2019	2020	2021	2022	2023	2024	2025	2026	2027	2028	2029	2030	2031	2032	2033	2034	2035	2036	2037	2038	2039	2040	2041	2042	2043	2044	2045	2046	2047	2048	2049	2050	2051	2052	2053	2054	2055	2056	2057	2058	2059	2060	2061	2062	2063	2064	2065	2066	2067	2068	2069	2070	2071	2072	2073	2074	2075	2076	2077	2078	2079	2080	2081	2082	2083	2084	2085	2086	2087	2088	2089	2090	2091	2092	2093	2094	2095	2096	2097	2098	2099	2100	2101	2102	2103	2104	2105	2106	2107	2108	2109	2110	2111	2112	2113	2114	2115	2116	2117	2118	2119	2120	2121	2122	2123	2124	2125	2126	2127	2128	2129	2130	2131	2132	2133	2134	2135	2136	2137	2138	2139	2140	2141	2142	2143	2144	2145	2146	2147	2148	2149	2150	2151	2152	2153	2154	2155	2156	2157	2158	2159	2160	2161	2162	2163	2164	2165	2166	2167	2168	2169	2170	2171	2172	2173	2174	2175	2176	2177	2178	2179	2180	2181	2182	2183	2184	2185	2186	2187	2188	2189	2190	2191	2192	2193	2194	2195	2196	2197	2198	2199	2200	2201	2202	2203	2204	2205	2206	2207	2208	2209	2210	2211	2212	2213	2214	2215	2216	2217	2218	2219	2220	2221	2222	2223	2224	2225	2226	2227	2228	2229	2230	2231	2232	2233	2234	2235	2236	2237	2238	2239	2240	2241	2242	2243	2244	2245	2246	2247	2248	2249	2250	2251	2252	2253	2254	2255	2256	2257	2258	2259	2260	2261	2262	2263	2264	2265	2266	2267	2268	2269	2270	2271	2272	2273	2274	2275	2276	2277	2278	2279	2280	2281	2282	2283	2284	2285	2286	2287	2288	2289	2290	2291	2292	2293	2294	2295	2296	2297	2298	2299	2300	2301	2302	2303	2304	2305	2306	2307	2308	2309	2310	2311	2312	2313	2314	2315	2316	2317	2318	2319	2320	2321	2322	2323	2324	2325	2326	2327	2328	2329	2330	2331	2332	2333	2334	2335	2336	2337	2338	2339	2340	2341	2342	2343	2344	2345	2346	2347	2348	2349	2350	2351	2352	2353	2354	2355	2356	2357	2358	2359	2360	2361	2362	2363	2364	2365	2366	2367	2368	2369	2370	2371	2372	2373	2374	2375	2376	2377	2378	2379	2380	2381	2382	2383	2384	2385	2386	2387	2388	2389	2390	2391	2392	2393	2394	2395	2396	2397	2398	2399	2400	2401	2402	2403	2404	2405	2406	2407	2408	2409	2410	2411	2412	2413	2414	2415	2416	2417	2418	2419	2420	2421	2422	2
--	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	---